

Skeet Power Supply Card

Terminals marked AC IN.....110 AC volt power cord to wall outlet; Line terminal for black (or brown) wire, NEU terminal for neutral white (or blue) wire.

Terminals marked Motor..... 110 AC power to the motor; Line terminal for black (or brown) wire, NEU terminal for neutral white (or blue) wire.

Terminals marked Pickle..... Pull Cord wires; POS (+) terminal for black wire for high house trap (green if hooking up low house), **NEG (-)** terminal for white common wire.

Terminals marked Radio 12+V..... 12 volt remote power supply; POS (+)terminal 12 v positive power, **NEG (-)** 12 V negative power.

Terminals marked Coil Trap ..Two terminals marked + & -, two wires from the selenoid need to be connected to these terminals.Polarity is not an issue; connect one wire to the plus terminal and the other wire to the negative terminal.

Terminals marked Coil Tap ..Two terminals marked + & -, two wires from the selenoid need to be connected to these terminals.Polarity is not an issue; connect one wire to the plus terminal and the other wire to the negative terminal.

